

Mitsubishi Melsec-L(Binary)

Refer to these sections for details:

- [Supported Series](#)
- [PLC Connection Settings](#)
- [PLC Configuration](#)
- [LoopEdge DeviceHub Configuration](#)
- [Device Addresses](#)

Supported Series

Mitsubishi Q series (Q03UDE, Q04UDEH, Q06UDEH, Q10UDEH, Q13UDEH, Q20UDEH, Q26UDEH), Mitsubishi L series(L02, L26-BT), MELSEC-Q/L protocol application to CPU of Ethernet interface or Ethernet module.

Website: <http://www.mitsubishi-automation.com/>

PLC Connection Settings

Parameters	Recommended	Options	Notes
PLC Type	Mitsubishi MELSEC-L - Binary Mode (Ethernet)		
PLC Interface	Ethernet		
Port #	4999	1025 to 4999 or 5010 to 65534	
Network #	0	0~255	
PLC Station #	255	255	
Protocol	TCP	TCP/UDP	MC Protocol

PLC Configuration


The setup shown here is for the Mitsubishi Melsec-L(Binary) module.

 Online Simulator: Yes

LoopEdge DeviceHub Configuration

To configure DeviceHub for this Mitsubishi Melsec-L PLC:

1. **DeviceHub > Add Device**
Type: Mitsubishi
Driver: Mitsubishi Melsec-L(Binary)



2. Enter details specific to your environment and click **Add Device**.

Add Device

Select Type: **Mitsubishi** Select Driver: **Mitsubishi Melsec-L(Binary)**

Name: _____
This is a Device Name.

Description: **mitsubishi device**
This is a description of device.

Network Address: **192.168.01** Network Port: **5002**
This is a IP Address of device. This is a network port of device.

Station Id: **255**

 Cancel

Device Addresses

Bit /Word	Device Type	Format	Range	Memo
B	X	HHHH	0 ~ 65536	Input Relay
B	Y	HHHH	0 ~ 65536	Output Relay
B	M	DDDDD	0 ~ 65535	Internal Relay
B	SM	DDDD	0 ~ 2047	Special Relay
B	L	DDDDD	0 ~ 32237	Latch Relay
B	F	DDDDD	0 ~ 32237	Annunciator
B	V	DDDDD	0 ~ 32237	Edge Relay
B	B	DDDDD	0 ~ 32237	Link Relay
B	TS	DDDDD	0 ~ 25471	Timer Contact
B	TC	DDDDD	0 ~ 25471	Timer Coil
B	SS	DDDDD	0 ~ 25471	Retentive Timer Contact

B	SC	DDDDD	0 ~ 25471	Retentive Timer Coil
B	CS	DDDDD	0 ~ 25471	Counter Contact
B	CC	DDDDD	0 ~ 25471	Counter Coil
B	SB	DDDDD	0 ~ 32237	Special Link Relay
B	S	DDDD	0 ~ 8191	Step Relay
B	DX	DDDD	0 ~ 8191	Direct Input
B	DY	DDDD	0 ~ 8191	Direct Output
W	D	DDDD	0 ~ 9999	Data Register
W	W	DDDD	0 ~ 8191	Link Register
W	TN	DDDDD	0 ~ 25471	Timer Current Value
W	SN	DDDD	0 ~ 25471	Retentive Timer Current Value
W	CN	DDDDD	0 ~ 25471	Counter Current Value
W	SD	DDDD	0 ~ 2047	Special Register
W	R	DDDD	0 ~ 9999	File Register
W	ZR	DDDDDD	0 ~ 999999	File Register
W	Z	DD	0 ~ 20	Index Register